

SUMMARY TABLE OF CONTROLS N-COM B901L R SERIES

<i>Button</i>		n	on	▲	▼	+ ▼
Basic Functions	Turning on		2 sec			
	Turning off		6 sec			
	Increase Volume			X		
	Decrease Volume				X	
	Management of Lights Menu					2 sec
Bluetooth Devices	Answer phone call*	X	X	X	X	
	Voice call		2 sec			
	Speed Dialling Menu**	X	X			
	Hang up/reject a phone call		2 sec			
	Manual Device Connection		2 sec			
	Phone Conference Activation CHANNEL 1	X				
	Phone Conference Activation CHANNEL 2	x2				
	Phone Conference Activation CHANNEL 3	x3				
	Turning off the Conference function	X				
Bluetooth Music / Cable	Play music (Play)		X			
	Pause Function (Pause)		X			
	Next track (Forward)			2 sec		
	Previous track (REW)				2 sec	
	Share A2DP music		X			
	Activate audio via cable		x3			
	Deactivate audio via cable		x3			
N-Com Intercom (900 series)	Connection CHANNEL 1	X				
	Disconnection of active intercom	X				
	Calling CHANNEL 2	x2				
	Calling CHANNEL 3	x3				
	Group intercom connection		2 sec			
	Group intercom disconnection	X				
Radio Menu	Turning on the Radio		x2			
	Turning off the Radio		x2			
	Automatic search for new station			2 sec		
	Change station (pre-set stations)				2 sec	
	Pre-set station				4 sec	

*Press any key on the N-Com keypad.

**Press the keys at the same time.